

Product Update

Title: Update firmware for the IP Control

No: 200706-02

Contact: mtu@minicom.com

Summary: IP Control firmware was recently updated to include product operation enhancements.

More Information

We updated the IP Control firmware to the version 3.0.1.39 which is available from our support web site at <http://www.minicom.com/phandlh.htm>

This version has following improvements:

- Video engine stability improvements.
- Changed keyboard LED synchronization mechanism.
- SDF update.

To update the firmware please follow these steps:

1. Ensure that IP Control is connected to computer or KVM switch and computer or KVM switch is switched on. Ensure that power supply of the computer or KVM switch and IP Control won't be interrupted during the update process.
2. Log on to IP Control configuration web page with administrator permissions:
<https://xxx.xxx.xxx.xxx/config> (where xxx.xxx.xxx.xxx is the IP Address of the unit)
3. From the menu select Firmware Upgrade. The Firmware Upgrade page appears
4. Locate and upload the file from your client system. (note: In case of any errors the upload will be aborted)
5. Verify the current IP Control firmware and newly uploaded firmware versions.
6. Press the 'Start Update' button. The IP Control starts to update the firmware.
Warning! This process is irreversible; ensure the IP Control power supply won't be interrupted during the update process, as this may cause damage to the unit.
7. When prompted press 'Reboot' button to reboot IP Control. One minute later, IP Control runs with the new firmware. You must login again.
8. **Warning!** The unit may lose all user configurations except IP Settings after firmware upgrade and may revert to the factory default settings (Except the network settings which will remain unchanged). Each release contains warning if all user settings would be lost or not.

After this firmware upgrade is applied to IP Control, all user settings, except network configuration will be erased after reboot.

Notes:

If you are using custom SDF with Scroll Lock or Num Lock switching hotkey, please request SDF update from Minicom Technical Support team